



17 Harry Pichanick Drive  
Alex Park  
Harare

Tel: + 263 4 744759  
Cell: +263 77 2 515919  
Cell: +27 82 856 0393

**Radzim Agri-Power**

## BUNDU POWER

**BP10S**

### GENERAL DATA

Model	BP10S
Continuous / Prime power (P.R.P)	10.0
Stand-by power (L.T.P)	11.0
Power Factor / Cos ( $\phi$ )	1.0
Frequency	50
Voltage	230
No. phases	Single Phase
Engine Speed	1500

### DIMENSIONS (UNPACKED)\*

Length (-L- m)	1620
Width (-W- m)	820
Height (-H- m)	1120
Weight (kg)	600
Tank Capacity	25

### CONTROL PANEL

Model	GU611
Type	Digital
Analogue Inputs	2
Mains Phase Voltage	Yes
Mains Line Voltage	Yes

### ENGINE

Brand	Bundu Power
Model	YD480D
Type	
Starting System	12 Volt Electric Starter
Auto-Decompression	Yes
Cubic Capacity (L)	1.357
Compression Ratio	18:1
Rated Power (kW/rpm)	12 / 1500
Fuel Type	Diesel
Lube Oil	L-ECD grade or 15W40
Low Pressure Alert	Yes
Low Fuel Cut Out	Yes

### ALTERNATOR

Model	WT-164B
Rated Current (A)	43.5
Pole Number	2
Excitation Mode	Brushless / Self Excitation



### ADDITIONAL

Running Time per Tank (Hr)	8.0 @ full load
Structure Type	Silent
Noise Level (dBA @ 7m)	< 68 - 70
Auto Voltage Regulator (AVR)	Constant voltage AVR
ISO9001 & CE Certified	Yes

\* Figures are subject to change without prior notice.

\*\* The mentioned power values are according to ISO8528-1 Standards

**RADZIM AGRI-POWER**