

17 Harry Pichanick Drive  
Alex Park  
Harare

Tel: + 263 4 744759  
Cell: +263 77 2 515919  
Cell: +27 82 856 0393



## Radzim Agri-Power

### PERKINS

### P21FOX

#### GENERAL DATA

Model	P21FOX
Continuous / Prime power (P.R.P)	20,00 kVA
Continuous / Prime power (P.R.P)	16,00 kW
Stand-by power (L.T.P)	21,80 kVA
Stand-by power (L.T.P)	17,44 kW
Power Factor / Cos (φ)	0.8
Frequency	50 Hz
Voltage	400/230 V
No. phases	Three Phases (with Neutral)
Engine Speed	1500 rpm

#### DIMENSIONS\*

Length (-L- m)	1555 mm
Width (-W- m)	760 mm
Height (-H- m)	1350 mm
Weight (kg)	670 kg
Tank Capacity	50 l

#### ENGINE

Brand	PERKINS
Model	404D-22G
No. of Cylinders	4
Cubic capacity	2,216 l
Air intake	Aspirated
Cooling	Water
Flywheel net power	18,4 kW
BMEP	
SAE:	

#### ENGINE TECHNICAL DATA

Oil Qty	
Antifreeze Qty	
Cooling air flow	
Combust. air flow	
Exhaust gas flow	

#### FUEL CONSUMPTION @ LOAD

100% (Standby)	6,2 l/h
100% (Prime)	5,4 l/h
75%	4 l/h
50%	2,9 l/h
25%	N/A



#### ALTERNATOR

Brand	SINCRO
Model	SK160MB
Continuous power	20 kVA
Stand-by power	21,8 kVA
Connection	Stella Series

#### STARTING BATTERY

Capacity	100 Ah
Quantity	1
Voltage	12 V

#### FLEXIBLE PIPE

Model	DN40
Quantity	1
Diameter	48 mm

#### EXHAUST SILENCER

Model	MSR/a 35
Quantity	1
Diameter	45 mm

\* Figures are subject to change without prior notice.

\*\* The mentioned power values are according to ISO8528-1 Standards